



3890 Oakwood Ave.
 Youngstown, OH 44515-3033
 Phone: (800) 239-1226
 US Fax: (877) 517-2586
 Intl. Fax: (858) 300-5327
 www.sensourceautomation.com

PC-QS06-D People Counter

The PC-QS06-D photoelectric sensor emits an invisible beam of light that travels across a maximum distance of 20ft (~6m) between the sensor and the reflector. When a person crosses this beam a digital signal is sent to the counter incrementing its display by +1. This unit counts up regardless of the direction of traffic (entering or exiting). Removal of power to the display does not reset the counter. It will maintain its count until the reset magnet is swiped across the reset area. This system operates with a safe 12V DC voltage.



Components (P/N: PC-QS06-D)

- MS-4 Reflector
- QS06 Sensor w/Bracket
- LCD Display
- Magnetic Reset tool
- 120VAC to 12VDC Power Adapter

Optional Components:

- PCDL-1000 Count Recorder
- XR9-CT1 (Wireless Data Transmitter)
- PCW-Chime Annunciator

Specifications:

Parameter

Sensor (w/Bracket)
 Sensing Distance
 Counter Display
 Reflector
 Reset
 Power Supply (not Shown)

Description

Infrared retroreflective (2.6L x 1.6W x 2.3H")
 20ft max. with MS-4 reflector (included)
 8-digit LCD with 3.3L x 3.3W x 1.25H" enclosure
 MS-4 3" round reflector with center mounting hole
 Magnetic reset
 120Vac to 12Vdc plug-in adapter with terminal screws